



by Honeywell

MS-7 Series

Description

The Gamewell-FCI, MS-7 Series manual fire alarm stations are available in a wide variety of configurations. The Stations comply with the Americans with Disabilities Act (ADA) 5-lb. maximum pull force requirement. Operating instructions and Braille text are engraved in the handle. All stations have a key lock/reset which is keyed alike with Gamewell-FCI fire alarm control panels and other manual fire alarm stations.

MS-7AF Velociti Addressable Station

The MS-7AF Velociti® Series addressable station is a double action station designed for installation in the signaling line circuit of Gamewell-FCI analog addressable control panels. Activation of the station causes its assigned address to register at the control panel. The door contains an LED which flashes green in normal condition and lights steady red when the station has been activated.* The station features screw terminals.

MS-7ASF Velociti Addressable Station

The MS-7ASF Velociti® Series addressable station is a single action station designed for installation in the signaling line circuit of Gamewell-FCI analog addressable control panels. Activation of the station causes its assigned address to register at the control panel. The door contains an LED which flashes green in normal condition and lights steady red when the station has been activated.* The station features screw terminals.

The Velociti® Series stations use a communication protocol that substantially increases the speed of communication between the sensors and certain Gamewell-FCI analog addressable fire alarm controls. These devices operate in a grouped fashion. If one of the devices in the group has a status change, the panel's microprocessor stops the group poll and focuses on the single device. The net effect is response speed up to five times greater than earlier designs.

MS-7 Double Action Station

The MS-7 double action station is used with conventional fire alarm control panels. It features a set of single pole contacts and screw terminals for connection to an initiating circuit.

Velociti® is a registered trademark of Honeywell International Inc.

UL® is a registered trademark of Underwriter's Laboratories Inc.

LEXAN® is a registered trademark of GE Plastics, a subsidiary of General Electric Company.

Non-Coded, Manual Fire Alarm Stations



MS-7

Features

- Addressable stations compatible with all Gamewell-FCI analog addressable fire alarm controls
 - Conventional stations suitable for use with any UL® Listed control panel
 - Both single and double action stations available
 - Tumbler lock for test and reset keyed alike with Gamewell-FCI controls
 - Surface or semi-flush mounting
 - Shock and vibration resistant
 - Stations (MS-7LOB) Listed for outdoor applications
 - Complies with ADA pull force requirements
- *Only the red LED is operative in panels that do not operate in Velociti mode.

SIGNALING



LISTED S2465

APPROVED 3023594

MEA Approved

67-02-E Vol.VIII



7150-1703:0119

7150-1703:0170

7150-1703:0109



GAMEWELL-FCI

12 Clintonville Road, Northford, CT 06472-1610 USA • Tel: (203) 484-7161 • Fax: (203) 484-7118

Specifications are for information only, are not intended for installation purposes, and are subject to change without notice. No responsibility is assumed by Gamewell-FCI for their use.

©2013 by Honeywell International Inc. All rights reserved.

www.gamewell-fci.com

9020-0616 Rev. E page 1 of 2

MS-7S Single Action Station

The MS-7S single action station is used with conventional fire alarm control panels. It features a set of single pole contacts and wire leads for connection to an initiating circuit.

MS-7SP Double Action Station

The MS-7SP is a double action station similar to the MS-7 station, with the additional feature of both English and Spanish instructions molded into the unit.

MS-7LR Dual-action Agent Release Station

The MS-7LR is designed for use with the Gamewell-FCI fire alarm control panels with releasing capabilities and Flex Series releasing systems. It features a set of single pole contacts and screw terminals for connection to an initiating circuit.

MS-7LRA Agent Release Station with Abort

The MS-7LRA is designed for use with the Gamewell-FCI fire alarm control panels with releasing capabilities and Flex Series releasing systems where system abort capabilities are required. It consists of an MS-7LR mounted on a plate with an abort switch and LED indicators for system normal, and system activated status.

MS-7LOB Double Action Station (Listed for Outdoor Applications)

The MS-7LOB station must be mounted on a Model SB-I/O backbox. In retrofit applications, the station is UL Listed for use with the WP-10 backbox. It is intended for use with conventional control panels and has a set of single pole contacts and screw terminals.

Mounting

The MS-7 interior stations may be surface mounted or semi-flush mounted on a standard double-gang, or 4-inch (10.2 cm) square electrical box. An optional trim ring (BG12TR) may also be used for semi-flush mounting.

NYC-Plate

The NYC-Plate provides the backplate for the manual pull station. (See Figure 1).



Figure 1 NYC-Plate

Specifications

Material:	Lexan®
Contact Ratings:	0.25 amps. @ 30 VAC/VDC (resistive)
Dimensions:	5 5/8" H x 4 1/4" W x 1 1/4" D (14 x 10.1 x 3.2 cm)
Operating Temperature	
(MS-7AF, MS-7ASF):	32° to 120° F (0° to 49° C)
(MS-7LOB):	-30° to 150° F (-35° to 66° C)
Relative Humidity	
(MS-7AF, MS-7ASF):	10 to 93% (non-condensing)
(MS-7LOB):	85% ± 5% @ 86° ± 3.6° (30° ± 2° C)
Alarm Current:	.0030 amp. 0.007 for LED
Supervisory Current	
(MS-7AF, MS-7ASF):	.00030 amps.

Ordering Information

Part Number	Description
MS-7	Double action station
MS-7AF**	Velociti addressable double action station
MS-7ASF**	Velociti addressable single action station
MS-7S	Single action station, wire leads
MS-7SP	Double action station, English and Spanish instructions
MS-7LR	Agent release station, dual-action
MS-7LRA	Agent release station with abort switch, LED indicators, dual-action
MS-7LOB	Double action station, outdoor use (Includes SB-I/O - Indoor/outdoor use backbox)
SB-I/O	Indoor/outdoor use backbackbox
SB-10	Surface backbox
BG12TR	Trim ring for semi-flush mount, plastic
NY-PLATE	NYC backplate for manual pull station

**For use with the Gamewell-FCI analog addressable control panels only.